HP LaserJet Pro M402dne



For More Information Unilimit 800-666-2980 Sales@UniLinkinc.com

www.UniLinkinc.com

Printing performance and robust security built for how you work. This capable printer finishes jobs faster and delivers comprehensive security to guard against threats.¹ Original HP Toner cartridges with JetIntelligence give you more pages.²

Print speed:Letter: Up to 40 ppm; First Page Out: As fast as 5.6 sec

Print Resolution: Black (best): HP FastRes 1200; Black: (Fine Lines): Up to 1200 x 1200 dpi Print Technology Resolution: HP FastRes 1200, HP ProRes 1200, 600 dpi

Standard Connectivity: 1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network Standard Memory:Standard: 256MB DRAM Mobile Printing Capability: HP ePrint, Apple AirPrint™, Morpria-certified, Google Cloud Print 2.0, Mobile Apps Paper Handling: 100-sheet multipurpose Tray 1, 250-sheet input Tray 2; 150-sheet output bin

Display:2-line backlit LCD graphic display













Fast printing. Strong protection.

- Grab pages and go—without waiting around. This printer wakes up and prints faster than the competition.¹
- Breeze through multipage documents with two-sided printing that's faster than the competition.
- Help keep printing safe from boot up to shutdown with security features that guard against complex threats.

More. Pages, Performance, and Protection.

- Get the most prints for your money—with Original HP High Yield Black Toner cartridges with JetIntelligence.²
- Count on consistent results at high speeds with precision black toner.
- Help ensure you're getting the authentic HP quality you paid for with innovative anti-fraud technology.
- Print right away with preinstalled toner cartridges. Replace them with optional high-yield cartridges.

Help save energy and easily manage tasks

- Help save energy with HP Auto-On/Auto-Off Technology.³
- Print using less energy than competitors—enhanced by Original HP Toner cartridges with JetIntelligence.⁴
- Make the most of your office space, with a printer that conveniently fits right into your work style.
- Easily manage devices and settings using HP Web Jetadmin with a suite of essential management features.⁵

Stay connected with easy mobile printing options

- Easily print from a variety of smartphones and tablets—generally no setup or apps required.⁶
- Easily set up, print, and share with built-in Ethernet networking.

¹ Based on HP internal testing of top three leading competitors' first page out from Sleep mode and duplex print speed completed 8/2015. Subject to device settings. Actual results may vary. For details see http://www.hp.com/go/Ljclaims. Automatic two-sided printing not available for the HP Laser Jet Pro M402n.² Based on cartridge yields for HP 80X compared with HP 26X Original HP Laser-let Toner Cartridges. For more information, see http://www.hp.com/go/learnaboutsupplies ³ HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; May require a firmware upgrade. ⁴ Based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in energystar.gov of top three leading competitors as of 8/2015. Actual results may vary. For details see http://www.hp.com/go/Ljclaims ⁵ HP Web Jetadmin is free and available for download at http://www.hp.com/go/webjetadmin⁶ Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at http://www.hp.com/go/mobileprinting

HP LaserJet Pro M402dne Specifications Table

Print Speed	· · · · · · · · · · · · · · · · · · ·		Windows OS compatible with In-Box Driver: Windows XP SP3 all 32-bit editions (XP Home, XP
Print Resolution	Letter: Up to 40 ppm black; ⁴ First Page Out: As fast as 5.6 sec black; ⁵ Black (best): HP FastRes 1200; Black: (Fine Lines): Up to 1200 x 1200 dpi	Compatible Operating Systems	Windows O Schultz Haussen and Schultz Hauss
Print Resolution Print Technology			
Print Technology Print Resolution Technologies	Laser		
	HP FastRes 1200, HP ProRes 1200, 600 dpi		
Print Cartridges Number Standard Print languages			
Printer Smart Software Features	HP PCL 5, HP PCL 6, HP postscript level 3 emulation, direct PDF (v 1.7) printing, URF, PCLM, PWG		OS X 10.10 Yosemite; Mobile OS (In-OS drivers): iOS, Android, Windows 8/8.1/10 RT; Linux OS
	Auto-duplex printing, N-up printing, collation, HP ePrint, Apple AirPrint [™] , Google Cloud, Print Mopria-ertifical, Instant-on Echnology, HP Auto-On/Auto-Off technology, JetIntelligence Cartridge Technology, Job Storage with PIN printing		(In-O5 HPLIP): Auto install: BOSS (3.0, 5.0), DEBIAN (6.0, 6.0.1, 6.0.2, 6.0.3, 6.0.4, 6.0.5, 6.0.6, 6.0.7, 6.0.8, 6.0.9, 6.0.10, 7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6), FEDORA (17, 18, 19, 20), LINUX MII (13, 14, 15, 16, 17), SUBE LINUX (122, 12.3, 13.1), UBUNTU (10.04, 11.10, 12.04, 12.10, 13.
Printer Management	Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP Imaging and Printing Security Center; HP Utility (Mac); HP Device Toolbox		13.10, 14.04, 14.10), Manual install: MANDRIVA LINUX (2010.0, 2011.0), MEPIS (6.0, 6.5, 7.0, 8.0), PCLINUXOS (2006, 2007.0, 2007, 2008, 2009.0, 2009), RED HAT (8.0, 9.0), RED HAT ENTERPRISE LINUX (5.0, 6.0, 7.0), SLACKWARE LINUX (9.0, 9.1, 10.0, 10.1, 10.2
Standard Connectivity	1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network		11, 12, 12.1), GOS (8.04.1), IGOS (1.0), LINPUS LINUX(9.4, 9.5), LINUX FROM SCRATCH (6); Oth OS: UNIX ⁹
Network Capabilities	Via built-in 10/100/1000Base-TX Ethernet, Gigabit; Auto-crossover Ethernet; Authentication via 802.1X	Compatible Network Operating Systems	Windows OS compatible with In-Box Driver: Windows Server 2003/2003 R2 32-bit (SP1/SP2) Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2008 32/64-bit (SP2)
Network Ready	Standard (built-in Gigabit Ethernet)		Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2008 R2 64-bit (SP1) Standard/Enterprise (+ Cluster & Terminal Services); Windows OS compatible with Universal
Wireless Capability	No		Print Driver (UPD) or Product-Specific drivers from HP.com: Windows Server 2003/2003 R2
Mobile Printing Capability	HP ePrint,Apple AirPrint™, Morpria-certified, Google Cloud Print 2.0, Mobile Apps		32-/64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2008/2008 R: 32-/64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2012/2012 R2 64-bit Standard/Foundation/Essentials/Datacenter (+ Cluster & Terminal Services), MS Windows Server 2012 R2 Terminal Services: Cltrix NenApp 7.5, Cltrix NenDesktop 7.0, Cltrix NenDesktop 7.5, MS Windows Server 2008 R2 SP1 Terminal Services: Cltrix NenApp 7.5, Cltrix NenDesktop 7.0, Cltrix XenDesktop 7.5, MS Windows Server 2008 R2 SP1 Terminal Services: Cltrix NenApp 6.5, Cltrix NenApp 6.5, Cltrix NenApp 5.5, Cltrix NenApp 5.5, MS Windows Server 2008 R2 SP1 Terminal Services: Cltrix NenApp 6.0, Cltrix NenApp 6.5, Cltrix NenApp 5.5, Cltrix NenApp 5.5, Cltrix NenApp 5.5, Cltrix NenApp 5.5, OF Server 2008 R2 SP1 Terminal Services: Cltrix NenApp 6.5, Cltrix NenApp 6.5, Cltrix NenApp 5.5, Cltr
Memory	Standard: 256MB DRAM; Maximum: 256MB DRAM		
Processor Speed	1200 MHz / Hard disk: None		
Duty Cycle	Monthly, letter: Up to 80,000 pages ⁶		
Recommended Monthly Page Volume	750 to 4000 ⁷		
Media Types Supported	Paper (plain, EcoFFICIENT, light, heavy, bond, colored, letterhead, preprinted, prepunched, recycled, rough); envelopes; labels; transparencies		
Media Weight Supported	Tray 1: 16 to 46.6 lb; Tray 2 and Optional 550-sheet Tray 3: 16 to 32 lb		
Media Sizes Supported	Tray 1: Letter, Legal, Executive, Envelope #10, Envelope Monarch, Custom size 4 x 6 in, 5 x 8 in, 10 x 15 in statement; Tray 2 & Tray 3: Letter, Legal, Executive, Custom Size, 5 x 8 in, statement		
Media Sizes Custom	Tray 1: 3 x 5 to 8.5 x 14 in; Tray 2 and 3: 4.13 x 5.85 to 8.5 x 14 in		
Paper Handling	100-sheet multipurpose Tray 1, 250-sheet input Tray 2; 150-sheet output bin; Duplex Options: Automatic(Standard); Envelope Feeder: No; Standard Paper Trays: 2; Input Capacities: Up to 350 sheets (Tray 1: up to 100 sheets; Tray 2: up to 250 sheets); Output Capacities: Up to 150 sheets; Up to 10 envelopes; Up to 75 sheets	Minimum System Requirements	Novelli IPrint Client v5.4 for WinXP (32-bit, 64-bit) PC: Windows 10 (32-bit/64-bit), Windows 8.1 (32-bit/64-bit), Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit): GHz processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port, Windows Vista (32-bit): 1 GHz 32-bit (x66) processor, 1 GB RAM (32-bit) 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port, Windows XP (32-bit) 52: Pentium 23 MHz processor, 512 MB RAM 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port, Windows Server 2003 (32-bit) (SP1 or greater), Windows Server 2003 R2 (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Windows Server 2008 (32-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit), Windows Server 2008 R2 (64-bit) (SP1): 1 GHz 64-bit (x64) processor, 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port Windows Server 2008 (82-bit) (SP1): 1 Greater), Windows Server 2008 R2 (64-bit), Windows Server 2008 R2 (64-bit) (SP1): 1 GHz 64-bit (x64) processor, 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port MAC 05X 10.8
What's in the box	CSJ91A HP LaserJet Pro M402dne; Preinstalled HP 26A Black LaserJet Toner Cartridge (~3100 pages); Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord		
Replacement Cartridges	HP 26A Black LaserJet Toner Cartridge (~3100 pages), CF226A; HP 26X Black LaserJet Toner Cartridge (~9000 pages), CF226X; HP 26XC Black LaserJet Toner Cartridge, CF226XC ¹		
Product Dimensions	W x D x H : 15 x 14.06 x 8.5 in ² ; Maximum : 15 x 25 x 9.5 in		
Product Weight	18.92 lb		
Warranty Features	One-year warranty, return to HP Authorized Service Provider		Mountain Lion; OS X 10.9 Mavericks; OS X 10.10 Yosemite; Internet; USB; 1 GB available hard disk space; OS compatible hardware (For OS hardware requirements see
Energy Efficiency Compliance	ENERGY STAR® certified; Blue Angel; EPEAT® Silver		http://www.apple.com)
Control Panel	2-line backlit LCD graphic display; Buttons (OK, Menu, Cancel, Back); LED indicator lights (Attention, Ready)	Power	Power Supply Type: Internal (built-in) power supply; Power Requirements: 110-volt input voltage: 110 to 127 VAC (+/- 10%), 50/50 Hz (+/- 2 Hz); 220-volt input voltage: 220 to 240 W (+/- 10%), 50/50 Hz (+/- 2 Hz) (Not dual voltage, power supply varies by part number with
Display Description	2-line backlit LCD graphic display		#option code identifier); Power Consumption: 591 watts (Active Printing), 6.1 watts (Ready),
Software Included	For Windows 7: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Update, HP Device Toolbox, HP Printer Status and Alerts, HP Product Improvement Study, Reconfigure your HP Device; Warranty and Legal Guide, User Guide; Por Windows 8+: HP Software Installer/Uninstaller, HP PCL-6 Printer Driver, HP Device Experience (DXP), Warranty and Legal Guide, User Guide, Reconfigure your HP Device; For Windows XP, Windows Vista and associated servers: HP Software Installer/Uninstaller, HP PCL-6 Printer Driver, Warranty and		 8 watts (Sleep), 0.6 watts (Auto-On/Auto-Off, via USB connectivity), 0.1 watts (Shutdown or Off)¹⁴
		Acoustics	Acoustic Power Emissions (active): 6.8 B(A); Acoustic Power Emissions (ready): Inaudible; Acoustic Pressure Emissions (active): 54 dB(A); Acoustic Pressure Emissions (ready): Inaudible ¹⁷
	Legal Guide, User Guide; For Mac OS: Welcome Screen (Directs users to http://www.HP.com or OS App Source for LaserJet Software)	Operating Environment	Operating Temperature Range: 59 to 90.5°F; Recommended Operating Temperature: 63. to 77°F; Storage Temperature Range: -4 to 104°F; Non-Operating Humidity Range: 10 to 90% RH; Operating Humidity Range: 10 to 80% RH; Recommended Humidity Operating
Fonts and Typefaces	84 scalable TrueType fonts		Range: 30 to 70% RH
For More Information		Security Management	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPv1 & SNMPv2 community password change HP ePrint: HTTPS with certificate validation, HTTP Basic Access Authentication, SASL authentication; Firewall and ACL; SNMPv3, 802.1X, Secure Boot
	www.UniLinkinc.com	Accessories	HP Laser Jet 550-sheet Feeder/Tray D9P29A; HP v222w 16GB Mini USB Drive POR81AA

UniLinkinc.com 800-666-2980 Sales@UniLinkinc.com Accessories HP LaserJet S50-sheet Feeder/Tray D9P29A; HP v222w 16GB Mini USB Drive PORB1AA HP Service and Support Options UBTMSE HP 3 year Next Business Day Exchange LaserJet M402 Service; UBTMZE HP 3 year Next Business Day LaserJet M402 Hardware Support; UBTMZE HP 4 year Next Business Day LaserJet M402 Hardware Support; UBTMZE HP 5 year Next Business Day LaserJet M402 Hardware Support; UBTM7PE HP 1 year Post Warranty Next Business Day LaserJet M402 Hardware Support; H3110E HP Network Install Inkjet/Personal LaserJet Service

I Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit http://www.hp.com/go/learnaboutsupplies 2 Without optional 550-sheet tray; Dimensions with optional 550-sheet tray; Dimensions options options options options options options options options options opt

© Copyright 2016 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Windows is a registered trademark of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.

